

# Release Notes

## FieldLynx Lite 1.93

|   |   |
|---|---|
| Obtaining Lynx Products and Information ..... | 1 |
| Obtaining Technical Support .....             | 1 |
| What's New .....                              | 2 |
| Scoreboard Improvements .....                 | 2 |
| LaserLynx Improvements .....                  | 3 |
| Rulebook Updates .....                        | 3 |

### Obtaining Lynx Products and Information

There are three ways to obtain Lynx products and information:

- » Go to the Lynx website (<http://www.finishlynx.com/product/>)
- » Call (978) 556-9780 and ask to speak with someone in sales, or
- » Send an email to...

Domestic Sales: [domsales@finishlynx.com](mailto:domsales@finishlynx.com)

International Sales: [intlsales@finishlynx.com](mailto:intlsales@finishlynx.com)

### Obtaining Technical Support

There are three ways to obtain technical support for Lynx products:

- » Go to the Lynx website (<http://www.finishlynx.com/support/>)
- » Find our latest video tutorials on YouTube (<https://www.youtube.com/c/FinishLynx/videos>)
- » Call (978) 556-9780 and ask to speak with someone in tech support, or
- » Send an email to...

Technical support: [support@finishlynx.com](mailto:support@finishlynx.com)



# What's New

## Scoreboard Improvements

### ResultTV - Display white/red (foul) flag

**FieldLynx** can be used to send trigger (F1=Foul; F2=Valid) information to **ResultTV** and show the status of an attempt (valid/foul) on a video display.

- » To show white/red (foul) flags to **ResultTV** using standard layouts:
  1. Create a scoreboard object using the *resultv\_results-trigger.lss* script
    - a. **Note:** In **ResultTV**, setup a new source using the *FieldLynx\_results.rss* and insert bitmap objects using trigger F1/F2. Set a time value to each trigger to remove the flag after x seconds. Foul.tga and Valid.tga samples are included with **ResultTV** 6.31.
  2. Select an athlete from the **Athlete List**.
  3. When **X** is entered to assign a foul to the athlete, trigger F1 is sent with the next scoreboard update.
  4. For a valid attempt, hit **Alt-M** to send the F2 trigger.
- » To show white/red (foul) flags to **ResultTV** using video display layouts:
  1. Create a scoreboard object using the *Resultv\_Video\_results-trigger.lss* script
    - a. In **ResultTV**, setup a new source using the *Video Display.rss* and open the *Video Display.rtv* layout.
  2. Select an athlete from the **Athlete List**.
  3. When **X** is entered to assign a foul to the athlete, the video display object will turn red. Every scoreboard update will toggle red/off.
  4. For a valid attempt, hit **Alt-M** to toggle between white/off.

### VeriLight

**VeriLight** is a multi-level signal tower that can be controlled from **FieldLynx** to show the foul status of each attempt.

- » To show green/red (foul) lights on **VeriLight** from **FieldLynx**:
  1. Create a scoreboard object using the *VeriLight.lss* script (default IP/Port: 192.168.0.99/10000).
  2. Select an athlete from the **Athlete List**.
  3. When **X** is entered to assign a foul to the athlete, **VeriLight** will turn red. **Alt-I** (Scoreboard|Initialize) to turn off.
  4. For a valid attempt, hit **Alt-M** to toggle between green/off.

### Advanced Scoreboard Settings Dialog

The **Scoreboard** tab of the **Preferences** dialog presents a new **Advanced** button which opens the *Advanced scoreboard settings* dialog. This dialog has two settings that default to ON (checked) and offer the legacy behavior.

- » **Send scoreboard data byte-by-byte (Legacy)** - when checked, a scoreboard update will be sent in multiple packets of data. When unchecked, a scoreboard update will package all data into a single packet.

- » **Send scoreboard data line-by-line (Legacy)** - when checked, each section of a script (e.g. ResultsHeader, Results, ResultsTrailer) is sent separately. When unchecked, related sections are be packaged together and sent in a single update.

**TIP:** VeriLight requires that both settings be unchecked.

#### New/Updated scripts (LSS)

- » [new] **ResultTV\_Video\_Results-360.lss** - designed for Video Display objects in ResultTV for the Lynx 360 display.
- » [new] **ResultTV\_Video\_Standings-360.lss** - designed for Video Display objects in ResultTV for the Lynx 360 display.
- » [new] **ResultTV\_Video\_Results-trigger.lss** - designed to show white/red (foul) flag for Video Display objects in ResultTV.
- » [updated] **ResultTV\_Video\_Results.lss** - updated to show the wind reading in the header row when available.
- » [new] **resultv\_results-trigger.lss** - designed to send triggers to ResultTV standard layouts and show white/red (foul) flag.

#### LaserLynx Improvements

- » Test measurements show precision down to the millimeter
- » Support for the Sokkia SET5A

#### Rulebook Updates

- » The high school rule book sets the rounding for discus and javelin to nearest inch (rounded down) regardless of the mark. Previously, this was only applied for marks < 100 feet.

